

PRODUCT FEATURES

- Ultra-secure Direct Mount to the door frame for strength and reliability
- Fully sealed and conformal coated for weatherproof operations
- Sealed 10 ft. [3.05m] jacketed, stranded conductor cable
- Automatic dual voltage no field adjustment required
- Instant release circuit no residual magnetism
- Noise suppression no interference with sensitive electronics
- Efficient, low power usage
- All ferrous metal surfaces plated for durability and rust resistance
- MagnaCare Lifetime Replacement
 No Fault Warranty

PRODUCT OPTIONS

- Flexible mounting options for
- Out-swing doors
- In-swing doors
- Metal, wood, Herculite or glass with aluminum frame
- BondSTAT magnetic bond sensor Patented
- Integrated door position switch

SPECIFICATIONS

- UL 10C Listed
- CAN4-S104, CAN/ULC-S533 Listed
- ANSI/UL 294 Listed
- CSA-C22.2 No.205 Listed
- ANSI/BHMA 156.23, Grade 1; E08501–500
- NFPA 101
- CSFM- California State Fire Marshal Approved
- MEA City of New York Approved
- CE:EN 50091-1, EN 61000-6-2 Approved
- NEMA: 4X
- IEC: IP66

Holding Force: 600lbs [272kg]

Dimensions:

Magnalock: 8"L x 1-5/8"D x 1-7/8"H **Strike:** 6-1/4"L x 1/2"D x 1-5/8"H

Electrical:

300mA at 12VDC 150mA at 24VDC


Operating Temperature:


-40 to +140F [-40 to +60C] Indoor or Outdoor use

Shipping Weight: 6lbs [2.72kg]

Finishes: US32D/630 - Satin Stainless Steel CL - Clear (Dress Cover) BK - Black (Dress Cover)

US32/629 - Polished Stainless (Dress Cover) US03/605 - Polished Brass (Dress Cover)







With unsurpassed durability, the M32 will last long after most buildings wear out. Applications include storage areas, rooms, and hallways where reliability, high durability and low-maintenance are required.

M32

SERIES


Indoor/Outdoor Traffic Control

600lbs Holding Force

The Ultimate in Magnalock® Reliability for

The M32 electromagnetic lock is ideal for traffic control in high-use areas within secured or monitored perimeters.

| >> MODELS | | PART # Description |
|-----------|------------------------------|----------------------|
| M32 | M32 Magnalock | |
| M32B | M32 - MBS | |
| M32BD | M32 - MBS, DPS | |
| M32D | M32 - DPS | |
| M32F | M32 - Face Drilled | |
| M32FB | M32 - Face Drilled, MBS | |
| M32FBD | M32 - Face Drilled, MBS, DPS | |
| M32FD | M32 - Face Drilled, DPS | |



21